

**SUMMARY**

A multi-function slimline remote control that can be used to manage the settings of multiple compatible battens individually.



**ON/OFF**  
Press the "On/off" button, the light keeps permanently on or off. Press "Auto Mode", "Reset" or "Apply" buttons to quit from this mode.

**Auto Mode**  
Press "Auto Mode" button, the sensor starts to work and all settings remain the same before the light gets switched on/off.

**Reset**  
1. Press "Reset" button, change brightness to max level.  
2. Press "Reset" button, products with DIP switch will be controlled by DIP switches; otherwise all the setting will be just initial, that is 100% detection range, hold time 5S, no stand-by time and daylight threshold disabled.

Flick after press any button

Flick only after press "Apply" button

**+/-**  
1. To adjust brightness 10-100% in on/off mode.  
2. To adjust highest brightness 60-100% in sensor mode.

**Start**  
Press "Start" to customize scene, users can change detection range, daylight threshold, holdtime, standby dimming level and standby period.

**Memory**  
1. Press "Memory" to save all the settings.  
2. The settings remained as the last time if not get resetted values.

**Apply**  
1. Press "Apply" to deliver the saved setting.  
2. Press "Apply" without "memory" will make all the setting one-time operation.  
3. Settings should be done within 30S, otherwise it exits memory mode.

Detection area (Press to define detection area 100%/75%/50%/25%.)

Hold time (Press to define holdtime 5s/30s/1min/3min /5min/10min/20min/30min .)

Stand-by dimming level (Press to define stand-by dimming level 10%/20%/30%/50%.)

Stand-by period (Press to define stand-by period 0s/10s/30s/1min/5min/10min/30min/+∞)  
Note: "0s" means no standby period; "+∞" means unlimited standby period.

Daylight threshold (Press to define daylight level 2Lux/10Lux/30Lux/50Lux/80Lux/120Lux/Disable.)  
Note: Disable means light will be turned on once sensor detects movement, regardless of the ambient lux.

**Test (2s)**  
The button "Test (2s)" is for testing purpose after commissioning. Pressing this button, the sensor goes to test mode (hold time is only 2s)

**PRODUCT DATA**

Order Code	213979
Compatibility	Stellar V Wide: 211025DS, 211026DS, 211025DEMS, 211026DEMS. Stellar V: 211023DS, 211024DS, 211024DEMS. Tempest V: 211021DS, 211022DS, 211033DS, 211021DEMS, 211022DEMS. Ark Microwave Sensor: 333409 Falcon Microwave Sensor: 333499.
Warranty	5 years

